

RT27 Necklace transmitter

The RT27 necklace transmitter has been specially adapted to the requirements of people in need of care. The large push button makes it easy to operate.

Switching electrical devices on and off with a 1-button operation or activating paging systems are among the standard application areas of this transmitter.

An LED indicates if the battery needs to be changed. If the battery is running low, a separate radio signal is transmitted which can be analyzed by a corresponding Easywave receiver.



RT27E5001-11-23K

Technical specifications

Coding	factory coding with Easywave telegram
Frequency	868.30 MHz
Channels	1
Range	typically 150 m in good free-field conditions
Power supply	1x 3V battery, CR2032
Operating indicator	LED
Operation	transmission lasts as long as the button is pressed (maximum 36 seconds)
Function	depends on the receiver (see models)
Protection degree	IP65
Operating temperature	-20 °C to +60 °C
Dimensions	Ø 41 x 13 mm
Weight	16 g (including battery, without necklace)
Color	anthracite gray similar to RAL 7016

Scope of delivery

- Necklace transmitter including battery
- Necklace (predetermined breaking point)
- Operating manual

Accessories (optional)


RT27-ACC-05-23P	Necklace (predetermined breaking point)
ACC-TOO-01-23P	Round housing key
ACC-SEA-01-00Px	O-ring seal



RT27-ACC-05-23P



ACC-TOO-01-23P



ACC-SEA-01-00Px

Models

Product numbers	Description	Function
RT27E5001-11-23K	Necklace transmitter 1-channel, anthracite gray, red button	1x PULSE